# LT-DPXL-150-180-5/6

#### VHF 50W 6-CAVITIES DUPLEXERS

The LT-DPXL-150-180-5/6 is a 6-cavity VHF duplexer operating in the 150-180 MHz band, providing 5 MHz channel spacing. Optimized for reliability and durability, it ensures clean separation of transmit and receive paths with minimal loss, supporting demanding RF communication environments.

# **Key Features**

- Frequency range: 150-180 MHz
- 5 MHz TX/RX channel spacing
- · 6 resonant cavities for high selectivity
- Isolation ≥75 dB for clean channel separation
- Insertion loss ≤1.5 dB
- Max input power: 50 W
- 50 Ω impedance, VSWR ≤1.40
- · Rugged, compact metal housing
- · Connectors available: N-Female / BNC-Female

Electrical Specifications	
Frequency Range	150– 180 MHz
Channel Spacing	5 MHz
Number of Cavities	6
Impedance	50 Ω
VSWR	≤1.40
Insertion Loss	≤1.5 dB (typical
	≤1.2 dB)
Isolation	≥75 dB
Max Input Power	50 W
Mechanical Specifications	
Connectors	N-F / BNC-F
Dimensions	218 × 190 × 40 mm
Weight	1.5 kg
<b>Environmental Specifications</b>	
Operating Temperature	−20 °C ~ +50 °C



## **Applications**

Base stations and repeater systems Public safety and emergency communications networks

Professional two-way radio infrastructure Transportation and utility communication systems

RF systems requiring reliable transmit/receive isolation

### **Ordering Information**

The duplexer series is available in the following models:

LT-DPXL-136-150-5/6 : VHF Duplexer, 136-150 MHz, 5 MHz spacing, 6 cavities, 50 W

LT-DPXL-150-180-5/6: VHF Duplexer, 150-180 MHz, 5 MHz spacing, 6 cavities, 50 W

LT-DPXL-400-450-5/6 : UHF Duplexer, 400-450 MHz, 5 MHz spacing, 6 cavities, 50 W

LT-DPXL-450-500-5/6 : UHF Duplexer, 450-500 MHz, 5 MHz spacing, 6 cavities, 50 W

#### **Notice**

Lamatel duplexers can be factory-tuned to the customer's specified operating frequencies prior to shipment. If the required frequencies are not provided at the time of order, the duplexer will be delivered in its standard untuned state. In such cases, the responsibility for tuning the duplexer to the desired frequencies rests with the customer.

