LT-DPXL-400-450-5/6

6-Cavity Duplexer | 400-450 MHz

The Lamatel LT-DPXL-400-450-5/6 6-Cavity Duplexer is designed for efficient frequency separation in the 400-450 MHz UHF band. Featuring a 6-cavity design, this duplexer ensures superior isolation between transmit and receive paths, minimizing signal interference and enhancing communication clarity. Its robust construction and tunable configuration make it ideal for base stations, repeaters, and other UHF communication systems where stable, high-performance operation is essential.

Key Features

- Frequency Range: 400-450 MHz UHF band
- · 6-Cavity Design for excellent TX/RX isolation
- · Low Insertion Loss ensures optimal signal quality
- High Power Handling Capability for demanding communication systems
- Tunable Screw Design for flexible frequency adjustments

Key Highlights

- Wide Frequency Coverage suitable for various UHF applications
- High Isolation Performance to prevent cross-talk and interference
- Compact Design for easy integration into communication systems
- Consistent Operation Across Temperature Ranges ensuring reliability in diverse environments
- Corrosion-Resistant Materials for extended service life
- Easy Field Tuning without the need for specialized tools

Applications

- Base Stations for UHF communication networks
- Repeaters in public safety, commercial, and industrial radio systems
- Two-Way Radio Systems for clear and reliable communication
- Emergency Services Communications (Police, Fire, EMS)



Specifications

| LT-DPXL-400-450-5/6 | |
|-----------------------|-------------------------|
| Product Type | UHF |
| Frequency Range | 400-450 MHz |
| VSWR | ≤1.35 |
| Bandwidth | ±100 (KHz) |
| Frequency Spacing | 5-7 (MHz) |
| Insertion Loss | ≤1.5 dB |
| No. of Cavity | 6 |
| Isolation | ≥75 dB |
| Maximum Input Power | 50 W |
| Normal Impedance | 50 Ω |
| Connector | N-F/BNC-F |
| Operating Temperature | -20°C - +50°C |
| Weight | 1.5 Kg |
| Dimensions | 218 x 190 x 40 (±0.5mm) |



LT-DPXL-400-450-5/6

6-Cavity Duplexer | 400-450 MHz



